

ECGR 4124 – Breadth Exam

Department of Electrical and Computer Engineering
University of North Carolina at Charlotte

Quiz Instructions

1. Question 1 – 3 pts

An LTI system has impulse response defined by $\{4, -2, 7\}$. Determine the output of the system $y[n]$ when the input $x[n] = \{1, -1, 2\}$. Provide a single number as your answer which is the total of the values of the output, i.e., $\text{sum}(y[n])$.

2. Question 2 – 3 pts

What components are typically needed to construct a DSP system that can take analog signals as input and produce analog output? (Choose all that apply)

Capacitor

Resistor

CPU

op amp

ADC

DAC

Inductor

3. Question 3 – 3 pts

If an input $\sin(5\pi t)$ is sampled with a frequency of 8 samples/sec, what is the discrete-time frequency in rad/sample? Provide answer with two decimal digits.

4. Question 4 – 3 pts

Let $x[n]$ denote samples from a continuous signal $x(t) = \cos(2\pi \cdot 1.5t)$. For a sampling interval of $T = 0.3$ sec/sample, find ω_0 (radians/sample).

5. Question 5 – 3 pts

How many of the following are periodic?

(1) $\cos(0.3\pi n)$

(2) $\sin(\pi n/5)$

(3) 4

(4) $e^{j2\pi n/9}$

6. Question 6 – 3 pts

If $X = 3 + 4j$ and $Y = 2 - j$, simplify (X/Y^*) and provide the result in $a + jb$ form.

7. Question 7 – 3 pts

(True/False) The signal $x[n] = \cos(\pi\sqrt{2} n)$ is periodic.

8. Question 8 – 3 pts

Which of the following are equivalent to $\cos(\omega n + \phi)$?

(a) $\cos(\omega n - \phi)$

(b) $\sin(\omega n + \phi)$

(c) $\cos(-\omega n - \phi)$

(d) None of the above

9. Question 9 – 3 pts

What is the phase angle (in radians) of the complex number $-2 + 2j$?

10. Question 10 – 3 pts

Given $x[n] = \{1, 2, 3\}$, $h[n] = \{1, 0, -1\}$, list all values of $y[n] = x[n]*h[n]$.

11. Question 11 – 3 pts

If $x[n] = \delta[n-2] + 3\delta[n-4]$, what is $x[4]$?

12. Question 12 – 3 pts

Two discrete-time sequences $x[n]$ and $h[n]$ have lengths 6 and 5, respectively. What is the maximum possible length of their linear convolution $y[n]$?

13. Question 13 – 3 pts


Let $x[n] = e^{(j3\pi n/8)}$. Find the fundamental period of $x[n]$.

14. Question 14 – 3 pts

Given $x[n] = u[n-5]$, determine the index n_0 where $x[n]$ first becomes 1.

15. Question 15 – 3 pts

A system has DTFT magnitude response shown below. Given $B=3$, indicate if the system is causal (1 = Yes, 0 = No). [Figure 1: magnitude plot included]



16. Question 16 – 3 pts

A system satisfies $y[n] = 2x[n-1] + 4x[n-3]$. Is it LTI? (1 = Yes, 0 = No)

17. Question 17 – 3 pts

For the system $y[n] = 0.8y[n-1] + x[n]$, determine if it is stable (1 = Yes, 0 = No).

18. Question 18 – 3 pts

If $X[k]$ is the DFT of $x[n]$, what is the phase of $X[4]$ if $X[4] = 3e^{j\pi/6}$?

19. Question 19 – 3 pts

If $x[n] = \delta[n] + \delta[n-2]$, find its DTFT $X(e^{j\omega})$.

20. Question 20 – 3 pts

A signal $x[n] = \cos(0.4\pi n)$ is sampled with $N=64$ for DFT. What index k corresponds to its main frequency component?

21. Question 21 – 3 pts

If $x(t) = \cos(200\pi t)$ is sampled with $T_s=2\text{ms}$, write $x[n]$.

22. Question 22 – 3 pts

A system that aliases frequencies is LTI? (True/False)

23. Question 23 – 3 pts

Given $x(t)$ with maximum frequency 250 Hz, what is the lowest sampling rate that avoids aliasing?

24. Question 24 – 3 pts

For $y[n] = 0.9y[n-1] + x[n]$, determine stability (1=Stable, 0=Unstable).

25. Question 25 – 5 pts

Compute $y[n] = x[n]*h[n]$ for $x[n]=\{1,2,1\}$, $h[n]=\{1,1,1\}$. Find $y[2]$.

26. Question 26 – 3 pts

The DFT of $x[n]$ is defined for $k=0, \dots, N-1$. If $N=128$, what is the frequency spacing $\Delta\omega$ in radians/sample?

27. Question 27 – 3 pts

If $x[n] = e^{j0.25\pi n} + e^{j0.5\pi n}$, what is its fundamental period?

28. Question 28 – 3 pts

Given $X[k] = \text{DFT}\{x[n]\}$, which operation on $x[n]$ causes a linear phase shift in $X[k]$?

29. Question 29 – 3 pts

If $x(t) = \sin(400\pi t)$ and is sampled at 300 Hz, will aliasing occur? (1=Yes, 0=No)

30. Question 30 – 3 pts

What sampling period T_s corresponds to $2 \times$ Nyquist rate for a signal of 400 Hz bandwidth?

31. Question 31 – 3 pts

A signal $x(t) = \cos(600\pi t) + \cos(1000\pi t)$. Find the minimum sampling rate to avoid aliasing.

32. Question 32 – 3 pts

Indicate if the system $y[n] = 0.5y[n-2] + 3x[n-1]$ is stable (1=Yes, 0=No).

33. Question 33 – 8 pts

Compute the convolution of $x[n]=\{1,0.5,-0.5\}$ and $h[n]=\{0.5,1,0.5\}$. Find $y[1]$. [Figure 2: Discrete-time waveform shown]

Figure 2: Example Discrete-Time Signal $x[n]$

